


DiCoder® CNS50: Motor Feedback System for installation in electric motors




Incremental signals with resolutions up to 4,096 lines per revolution and commutation signals are available. Select the motor feedback system to suit your individual requirements.

Possible product variations:


- Plug-in shaft or tapered shaft with different stator supports
- 2 to 8 pole pairs



DiCoder CNS50 series of motor feedback systems are used world-wide in many different applications and environments.

	<p>Number of lines 1,000 up to 4,096</p>
<p>Motor Feedback System</p>	




 **Number of lines**
1,000 up to 4,096

Motor Feedback System

- Output driver for incremental signals and commutation signals to EIA 422
- Working temperature range up to + 100 °C
- Two square-wave signals (90° off-set), reference pulse and the respective inverted signals
- Commutation signals R, S, T

Dimensional drawing CNS50, rubber support \varnothing 50




General tolerances to DIN ISO 2768-mk

PIN and wire allocation/16 pin connector

PIN	Signal	Colour of Wires	Explanation
1	GND	blue	Ground connection
2	R	white/green	Commutation signal
3	S	white/yellow	Commutation signal
4	T	white/grey	Commutation signal
5	Z	violet	Reference signal
6	B	pink	Incremental signal
7	A	white	Incremental signal
8	N. C.	–	Not connected
9	U_s	red	Supply voltage 5 V \pm 10 %
10	\bar{R}	white/pink	Commutation signal inverted
11	\bar{S}	white/blue	Commutation signal inverted
12	\bar{T}	white/red	Commutation signal inverted
13	\bar{Z}	yellow	Reference signal inverted
14	\bar{B}	black	Incremental signal inverted
15	\bar{A}	brown	Incremental signal inverted
16	N. C.	–	Not connected

Caution: Pins labelled "N. C." must not be occupied!

The encoder housing must be connected to the screen. Use the screen connection strand (200 mm, supplied) for this. It is included in the supply.



View of the plug-in face

Accessories

Connection technology

Technical Data according to DIN 32878		Plug-in Shaft CNS50	CNS										
Number of lines per revolution		1,000, 1,024, 2,000, 2,048, 4,000, 4,096											
Commutation signals		(See diagram, page 4) other commutation on request											
Dimensions		mm (see dimensional drawing)											
Mass		0.1 kg											
Inertial rotor moment		10 gcm ²											
Measurement step		90°/number of lines											
Reference signal	No. off	1											
	Position	90° electr., logically linked with A and B											
Max. operating speed		9,000 min ⁻¹											
Working speed		6,000 min ⁻¹											
Max. angular acceleration		0.2 x 10 ⁶ 1/s ²											
Operating torque		0.2 Ncm											
Starting torque		0.4 Ncm											
Permissible shaft movement													
static	radial/axial	± 0.5 mm/± 0.75 mm											
dynamic	radial/axial	± 0.05 mm/± 0.25 mm											
Angular motion, perpendicular to the rotational axis													
static		± 0.005 mm/mm											
dynamic		± 0.0025 mm/mm											
Life of ball bearings		3.6 x 10 ⁹ revolutions											
Working temperature range		0 ... + 100 °C											
Storage temperature range ¹⁾		- 40 ... + 125 °C											
Permissible relative humidity ²⁾		90 %											
Resistance													
to shocks ³⁾		100/10 g/ms											
to vibration ⁴⁾		20/10 ... 2000 g/Hz											
Protection class acc. IEC 60529 ⁵⁾		IP 40											
EMC ⁶⁾													
Operating voltage range		5 V ± 10 %											
Max. operating current, no load		50 mA											
Interface details:													
Output driver		EIA Standard RS 422											
Output signal sequence		See pulse-time diagram (page 4)											
Signal tolerance													
tx1 ... tx4 max. at 300 kHz		1.5 x 1/4 T											

¹⁾ Without packaging

²⁾ Condensation not permissible

³⁾ To DIN EN 60068-2-27

⁴⁾ To DIN EN 60068-2-6

⁵⁾ With mating connector inserted


⁶⁾ To DIN EN 61000-6-2 and DIN 61000-6-3

The EMC according to the standards quoted is achieved when the motor feedback system is mounted in an electrically conductive housing, which is connected to the central earthing point of the motor controller via a cable screen. This is also where the GND (0 V) connection of the supply voltage is linked to earth.

Users must perform their own tests when other screen designs are used.

Incremental signals

At constant speed, looking at the input shaft, and clockwise rotation.



By linking the two signals A and B, an output signal is created whose cycle durations $tx_1 \dots tx_4$ have different sizes.

The differences are determined:


1. by the mark/space ratio tolerance of the individual channels

2. by the tolerance in the 90° phase shift between A and B
3. by the frequency

Ideally, the times $tx_1 \dots tx_4$ should always be $1/4$ of the cycle duration T .

The typical output frequency of the encoder is defined such that the max. time tx is smaller than $1.5 \times T/4$.

Pulse-time diagram



Pole pairs	Number of poles	e, f, g, h, i, k	α
2	4	30°	180°
3	6	20°	120°
4	8	15°	90°
6	12	10°	60°
8	16	$7,5^\circ$	45°

The angular data is related to a mechanical shaft rotation.

Precision of the signals R, S, T $\pm 1^\circ$.

Ordering information CNS50

Motor Feedback System CNS50 with plug-in shaft, diameter 7 mm

Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	A				X		

Type of connection		Lines per revolution		Pole pairs	
Connector	= A	1,000	= 01	2 pole pairs	= 02
Stranded cable	= V	1,024	= 10	3 pole pairs	= 03
		2,000	= 02	4 pole pairs	= 04
		2,048	= 11	6 pole pairs	= 06
		4,000	= 04	8 pole pairs	= 08
		4,096	= 12		

Ordering example: Motor Feedback System CNS50, plug-in Shaft 7 mm, rubber support Ø 50

4,096 lines, 3 pole pairs, connector exit


Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	A	A	1	2	X	0	3

Please enter your individual encoder here

Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	A				X		

Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	A				X		


Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	A				X		

 **Number of lines**
1,000 up to 4,096

Motor Feedback System

- Output driver for incremental signals and commutation signals to EIA 422
- Working temperature range up to + 100 °C
- Two square-wave signals (90° offset), reference pulse and the respective inverted signals
- Commutation signals R, S, T

Dimensional drawing CNS50, spring mounting support Ø 66





General tolerances to DIN ISO 2768-mk

PIN and wire allocation/16 pin connector

PIN	Signal	Colour of Wires	Explanation
1	GND	blue	Ground connection
2	R	white/green	Commutation signal
3	S	white/yellow	Commutation signal
4	T	white/grey	Commutation signal
5	Z	violet	Reference signal
6	B	pink	Incremental signal
7	A	white	Incremental signal
8	N. C.	–	Not connected
9	U_s	red	Supply voltage 5 V ± 10 %
10	\bar{R}	white/pink	Commutation signal inverted
11	\bar{S}	white/blue	Commutation signal inverted
12	\bar{T}	white/red	Commutation signal inverted
13	\bar{Z}	yellow	Reference signal inverted
14	\bar{B}	black	Incremental signal inverted
15	\bar{A}	brown	Incremental signal inverted
16	N. C.	–	Not connected

Caution: Pins labelled "N. C." must not be occupied!

The encoder housing must be connected to the screen. Use the screen connection strand (200 mm, supplied) for this. It is included in the supply.



Accessories

Connection technology

Technical Data according to DIN 32878		Tapered Shaft CNS50	CNS										
Number of lines per revolution		1,000, 1,024, 2,000, 2,048, 4,000, 4,096											
Commutation signals		(See diagram, page 8) other commutation on request											
Dimensions		mm (see dimensional drawing)											
Mass		0.1 kg											
Inertial rotor moment		10 gcm ²											
Measurement step		90°/number of lines											
Reference signal	No. off	1											
	Position	90° electr., logically linked with A and B											
Max. operating speed		9,000 min ⁻¹											
Working speed		6,000 min ⁻¹											
Max. angular acceleration		0.2 x 10 ⁶ 1/s ²											
Operating torque		0.2 Ncm											
Starting torque		0.4 Ncm											
Permissible shaft movement													
static	radial/axial	± 0.5 mm/± 0.75 mm											
dynamic	radial/axial	± 0.05 mm/± 0.25 mm											
Angular motion, perpendicular to the rotational axis													
static		± 0.005 mm/mm											
dynamic		± 0.0025 mm/mm											
Life of ball bearings		3.6 x 10 ⁹ revolutions											
Working temperature range		0 ... + 100 °C											
Storage temperature range ¹⁾		- 40 ... + 125 °C											
Permissible relative humidity ²⁾		90 %											
Resistance													
to shocks ³⁾		100/10 g/ms											
to vibration ⁴⁾		20/10 ... 2000 g/Hz											
Protection class acc. IEC 60529 ⁵⁾		IP 40											
EMC ⁶⁾													
Operating voltage range		5 V ± 10 %											
Max. operating current, no load		50 mA											
Interface details:													
Output driver		EIA Standard RS 422											
Output signal sequence		See pulse-time diagram (page 8)											
Signal tolerance													
tx1 ... tx4 max. at 300 kHz		1.5 x 1/4 T											

¹⁾ Without packaging

²⁾ Condensation not permissible

³⁾ To DIN EN 60068-2-27

⁴⁾ To DIN EN 60068-2-6

⁵⁾ With mating connector inserted


⁶⁾ To DIN EN 61000-6-2 and DIN 61000-6-3

The EMC according to the standards quoted is achieved when the motor feedback system is mounted in an electrically conductive housing, which is connected to the central earthing point of the motor controller via a cable screen. This is also where the GND (0 V) connection of the supply voltage is linked to earth.

Users must perform their own tests when other screen designs are used.

Incremental signals

At constant speed, looking at the input shaft, and clockwise rotation.



By linking the two signals A and B, an output signal is created whose cycle durations $tx_1 \dots tx_4$ have different sizes.

The differences are determined:


1. by the mark/space ratio tolerance of the individual channels

2. by the tolerance in the 90° phase shift between A and B
3. by the frequency

Ideally, the times $tx_1 \dots tx_4$ should always be $1/4$ of the cycle duration T .

The typical output frequency of the encoder is defined such that the max. time tx is smaller than $1.5 \times T/4$.

Pulse-time diagram



Pole pairs	Number of poles	e, f, g, h, i, k	α
2	4	30°	180°
3	6	20°	120°
4	8	15°	90°
6	12	10°	60°
8	16	$7,5^\circ$	45°

The angular data is related to a mechanical shaft rotation.

Precision of the signals R, S, T $\pm 1^\circ$.

Ordering information CNS50

Motor Feedback System CNS50 with tapered shaft

Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	F				X		

Type of connection		Lines per revolution		Pole Pairs	
Connector	= A	1,000	= 01	2 pole pairs	= 02
Stranded cable	= V	1,024	= 10	3 pole pairs	= 03
		2,000	= 02	4 pole pairs	= 04
		2,048	= 11	6 pole pairs	= 06
		4,000	= 04	8 pole pairs	= 08
		4,096	= 12		

Ordering example: Motor Feedback System CNS50, tapered shaft, spring mounting support Ø 66

4,096 lines, 3 pole pairs, connector exit


Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	F	A	1	2	X	0	3

Please enter your individual encoder here

Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	F				X		

Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	F				X		


Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	F				X		

 **Number of lines**
1,000 up to 4,096

Motor Feedback System

- Output driver for incremental signals and commutation signals to EIA 422
- Working temperature range up to + 100 °C
- Two square-wave signals (90° off-set), reference pulse and the respective inverted signals
- Commutation signals R, S, T

Dimensional drawing CNS50, resolver support Ø 52




PIN and wire allocation/16 pin connector

PIN	Signal	Colour of Wires	Explanation
1	GND	blue	Ground connection
2	R	white/green	Commutation signal
3	S	white/yellow	Commutation signal
4	T	white/grey	Commutation signal
5	Z	violet	Reference signal
6	B	pink	Incremental signal
7	A	white	Incremental signal
8	N. C.	–	Not connected
9	U _s	red	Supply voltage 5 V ± 10 %
10	\bar{R}	white/pink	Commutation signal inverted
11	\bar{S}	white/blue	Commutation signal inverted
12	\bar{T}	white/red	Commutation signal inverted
13	\bar{Z}	yellow	Reference signal inverted
14	\bar{B}	black	Incremental signal inverted
15	\bar{A}	brown	Incremental signal inverted
16	N. C.	–	Not connected

Caution: Pins labelled "N. C." must not be occupied!

The encoder housing must be connected to the screen. Use the screen connection strand (200 mm, supplied) for this. It is included in the supply.



Accessories
Connection technology

Technical Data according to DIN 32878		Tapered Shaft CNS50	CNS									
Number of lines per revolution		1,000, 1,024, 2,000, 2,048, 4,000, 4,096										
Commutation signals		(See diagram, page 12) other commutation on request										
Dimensions		mm (see dimensional drawing)										
Mass		0.1 kg										
Inertial rotor moment		10 gcm ²										
Measurement step		90°/number of lines										
Reference signal	No. off	1										
	Position	90° electr., logically linked with A and B										
Max. operating speed		9,000 min ⁻¹										
Working speed		6,000 min ⁻¹										
Max. angular acceleration		0.2 x 10 ⁶ 1/s ²										
Operating torque		0.2 Ncm										
Starting torque		0.4 Ncm										
Permissible shaft movement												
static	radial/axial	± 0.25 mm/± 0.75 mm										
dynamic	radial/axial	± 0.05 mm/± 0.25 mm										
Angular motion, perpendicular to the rotational axis												
static		± 0.005 mm/mm										
dynamic		± 0.0025 mm/mm										
Life of ball bearings		3.6 x 10 ⁹ revolutions										
Working temperature range		0 ... + 100 °C										
Storage temperature range ¹⁾		- 40 ... + 125 °C										
Permissible relative humidity ²⁾		90 %										
Resistance												
to shocks ³⁾		100/10 g/ms										
to vibration ⁴⁾		20/10 ... 2000 g/Hz										
Protection class acc. IEC 60529 ⁵⁾		IP 40										
EMC ⁶⁾												
Operating voltage range		5 V ± 10 %										
Max. operating current, no load		50 mA										
Interface details:												
Output driver		EIA Standard RS 422										
Output signal sequence		See pulse-time diagram (page 12)										
Signal tolerance												
tx1 ... tx4 max. at 300 kHz		1.5 x 1/4 T										

¹⁾ Without packaging

²⁾ Condensation not permissible

³⁾ To DIN EN 60068-2-27

⁴⁾ To DIN EN 60068-2-6

⁵⁾ With mating connector inserted


⁶⁾ To DIN EN 61000-6-2 and DIN 61000-6-3

The EMC according to the standards quoted is achieved when the motor feedback system is mounted in an electrically conductive housing, which is connected to the central earthing point of the motor controller via a cable screen. This is also where the GND (0 V) connection of the supply voltage is linked to earth.

Users must perform their own tests when other screen designs are used.

Incremental signals

At constant speed, looking at the input shaft, and clockwise rotation.



By linking the two signals A and B, an output signal is created whose cycle durations $tx_1 \dots tx_4$ have different sizes.

The differences are determined:


1. by the mark/space ratio tolerance of the individual channels

2. by the tolerance in the 90° phase shift between A and B
3. by the frequency

Ideally, the times $tx_1 \dots tx_4$ should always be $1/4$ of the cycle duration T .

The typical output frequency of the encoder is defined such that the max. time tx is smaller than $1.5 \times T/4$.

Pulse-time diagram



Pole pairs	Number of poles	e, f, g, h, i, k	α
2	4	30°	180°
3	6	20°	120°
4	8	15°	90°
6	12	10°	60°
8	16	$7,5^\circ$	45°

The angular data is related to a mechanical shaft rotation.

Precision of the signals R, S, T $\pm 1^\circ$.

Ordering information CNS50

Motor Feedback System CNS50 with tapered shaft

Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	G				X		

Type of connection	Lines per revolution	Pole Pairs
Connector = A	1,000 = 01	2 pole pairs = 02
Stranded cable = V	1,024 = 10	3 pole pairs = 03
	2,000 = 02	4 pole pairs = 04
	2,048 = 11	6 pole pairs = 06
	4,000 = 04	8 pole pairs = 08
	4,096 = 12	

Ordering Example: Motor Feedback System CNS50, tapered shaft, resolver support Ø 52

4,096 lines, 3 pole pairs, connector exit

Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	G	A	1	2	X	0	3

Please enter your individual encoder here

Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	G				X		

Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	G				X		


Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	G				X		

Number of lines
1,000 up to 4,096

Motor Feedback System

- Output driver for incremental signals and commutation signals to EIA 422
- Working temperature range up to + 100 °C
- Two square-wave signals (90° offset), reference pulse and the respective inverted signals
- Commutation signals R, S, T

Dimensional drawing CNS50, rubber support Ø 50




General tolerances to DIN ISO 2768-mk

PIN and wire allocation/16 pin connector

PIN	Signal	Colour of Wires	Explanation
1	GND	blue	Ground connection
2	R	white/green	Commutation signal
3	S	white/yellow	Commutation signal
4	T	white/grey	Commutation signal
5	Z	violet	Reference signal
6	B	pink	Incremental signal
7	A	white	Incremental signal
8	N. C.	–	Not connected
9	U _s	red	Supply voltage 5 V ± 10 %
10	\bar{R}	white/pink	Commutation signal inverted
11	\bar{S}	white/blue	Commutation signal inverted
12	\bar{T}	white/red	Commutation signal inverted
13	\bar{Z}	yellow	Reference signal inverted
14	\bar{B}	black	Incremental signal inverted
15	\bar{A}	brown	Incremental signal inverted
16	N. C.	–	Not connected

Caution: Pins labelled "N. C." must not be occupied!

The encoder housing must be connected to the screen. Use the screen connection strand (200 mm, supplied) for this. It is included in the supply.



Accessories

Connection technology



Technical Data according to DIN 32878		Tapered Shaft CNS50	CNS									
Number of lines per revolution		1,000, 1,024, 2,000, 2,048, 4,000, 4,096										
Commutation signals		(See diagram, page 16) other commutation on request										
Dimensions		mm (see dimensional drawing)										
Mass		0.1 kg										
Inertial rotor moment		10 gcm ²										
Measurement step		90°/number of lines										
Reference signal	No. off	1										
	Position	90° electr., logically linked with A and B										
Max. operating speed		9,000 min ⁻¹										
Working speed		6,000 min ⁻¹										
Max. angular acceleration		0.2 x 10 ⁶ 1/s ²										
Operating torque		0.2 Ncm										
Starting torque		0.4 Ncm										
Permissible shaft movement												
static	radial/axial	± 0.5 mm/± 0.75 mm										
dynamic	radial/axial	± 0.05 mm/± 0.25 mm										
Angular motion, perpendicular to the rotational axis												
static		± 0.005 mm/mm										
dynamic		± 0.0025 mm/mm										
Life of ball bearings		3.6 x 10 ⁹ revolutions										
Working temperature range		0 ... + 100 °C										
Storage temperature range ¹⁾		- 40 ... + 125 °C										
Permissible relative humidity ²⁾		90 %										
Resistance												
to shocks ³⁾		100/10 g/ms										
to vibration ⁴⁾		20/10 ... 2000 g/Hz										
Protection class acc. IEC 60529 ⁵⁾		IP 40										
EMC ⁶⁾												
Operating voltage range		5 V ± 10 %										
Max. operating current, no load		50 mA										
Interface details:												
Output driver		EIA Standard RS 422										
Output signal sequence		See pulse-time diagram (page 16)										
Signal tolerance												
tx1 ... tx4 max. at 300 kHz		1.5 x 1/4 T										

¹⁾ Without packaging

²⁾ Condensation not permissible

³⁾ To DIN EN 60068-2-27

⁴⁾ To DIN EN 60068-2-6

⁵⁾ With mating connector inserted


⁶⁾ To DIN EN 61000-6-2 and DIN 61000-6-3

The EMC according to the standards quoted is achieved when the motor feedback system is mounted in an electrically conductive housing, which is connected to the central earthing point of the motor controller via a cable screen. This is also where the GND (0 V) connection of the supply voltage is linked to earth.

Users must perform their own tests when other screen designs are used.

Incremental signals

At constant speed, looking at the input shaft, and clockwise rotation.



By linking the two signals A and B, an output signal is created whose cycle durations $tx_1 \dots tx_4$ have different sizes.

The differences are determined:


1. by the mark/space ratio tolerance of the individual channels

2. by the tolerance in the 90° phase shift between A and B
3. by the frequency

Ideally, the times $tx_1 \dots tx_4$ should always be $1/4$ of the cycle duration T.

The typical output frequency of the encoder is defined such that the max. time tx is smaller than $1.5 \times T/4$.

Pulse-time diagram



Pole pairs	Number of poles	e, f, g, h, i, k	α
2	4	30°	180°
3	6	20°	120°
4	8	15°	90°
6	12	10°	60°
8	16	$7,5^\circ$	45°

The angular data is related to a mechanical shaft rotation.

Precision of the signals R, S, T $\pm 1^\circ$.

Ordering information CNS50

Motor Feedback System CNS50 with tapered shaft

Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	E				X		

Type of connection		Lines per revolution		Pole Pairs	
Connector	= A	1,000	= 01	2 pole pairs	= 02
Stranded cable	= V	1,024	= 10	3 pole pairs	= 03
		2,000	= 02	4 pole pairs	= 04
		2,048	= 11	6 pole pairs	= 06
		4,000	= 04	8 pole pairs	= 08
		4,096	= 12		

Ordering example: Motor Feedback System CNS50, tapered shaft, rubber support Ø 50

4,096 lines, 3 pole pairs, connector exit

Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	E	A	1	2	X	0	3

Please enter your individual encoder here

Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	E				X		


Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	E				X		

Position 1	Position 2	Position 3	Position 4	Position 5	Position 6	Position 7	Position 8	Position 9	Position 10	Position 11	Position 12	Position 13	Position 14
C	N	S	5	0	-	A	E				X		

Dimensional drawings and ordering information

Stranded cable/connector , straight, 14 wires, 14 x 0.24 mm²

Type	Part no.	Contacts	Wire length
DOL-OB14-GOM2XB3	2031082	16	0.2 m



Australia

Phone +61 3 9497 4100
1800 33 48 02 – tollfree
E-Mail sales@sick.com.au

Belgium/Luxembourg

Phone +32 (0)2 466 55 66
E-Mail info@sick.be

Brasil

Phone +55 11 5091-4900
E-Mail sac@sick.com.br

Ceská Republika

Phone +420 2 57 91 18 50
E-Mail sick@sick.cz

China

Phone +852-2763 6966
E-Mail ghk@sick.com.hk

Danmark

Phone +45 45 82 64 00
E-Mail sick@sick.dk

Deutschland

Phone +49 (0)2 11 53 01-250
E-Mail info@sick.de

España

Phone +34 93 480 31 00
E-Mail info@sick.es

France

Phone +33 1 64 62 35 00
E-Mail info@sick.fr

Great Britain

Phone +44 (0)1727 831121
E-Mail info@sick.co.uk

India

Phone +91-22-2822 7084
E-Mail info@sick-india.com

Italia

Phone +39 011 79 79 65
E-Mail info@sick.it

Japan

Phone +81 (0)3 3358 1341
E-Mail info@sick.jp

Nederlands

Phone +31 (0)30 229 25 44
E-Mail info@sick.nl

Norge

Phone +47 67 81 50 00
E-Mail austefjord@sick.no

Österreich

Phone +43 (0)22 36 62 28 8-0
E-Mail office@sick.at

Polska

Phone +48 22 837 40 50
E-Mail info@sick.pl

Republic of Korea

Phone +82-2 786 6321/4
E-Mail kang@sickkorea.net

Republika Slovenija

Phone +386 (0)1-47 69 990
E-Mail office@sick.si

Russia

Phone +7 95 775 05 30
E-Mail info@sick-automation.ru

Schweiz

Phone +41 41 619 29 39
E-Mail contact@sick.ch

Singapore

Phone +65 6744 3732
E-Mail admin@sicksgp.com.sg

Suomi

Phone +358-9-25 15 800
E-Mail sick@sick.fi

Sverige

Phone +46 8 680 64 50
E-Mail info@sick.se

Taiwan

Phone +886 2 2365-6292
E-Mail sickgrc@ms6.hinet.net

Türkiye

Phone +90 216 587 74 00
E-Mail info@sick.com.tr

USA

Phone +1 937-454-1956
E-Mail sales@stegmann.com

More representatives and agencies
in all major industrial nations at
www.sick.com

SICK | STEGMANN

SICK AG • Industrial Sensors • Waldkirch • Germany • www.sick.com
SICK STEGMANN GmbH • Donaueschingen • Germany • www.sick-stegmann.de

AUDIN - 8, avenue de la malle - 51370 Saint Brice Courcelles
Tel : 03.26.04.20.21 - Fax : 03.26.04.28.20 - Web : <http://www.audin.fr> - Email : info@audin.fr